

PILOT ZAMIENNIK ADV32L1 Setting Table

ELMIX-W.LIS

00138 WARSZAWA PL. MIROWSKI 1/ 30

TEL. 602237012/piloty-sklep@wp.pl



Layout Keys	TV
	Brand:VIEWPIA Model:ADV32L1
	Code Name
POWER	POWER
MUTE	MUTE
PREV/LIST	List
NEXT/USB	
i+/INFO	AUDIO I/II
INPUT/AV	INPUT/AV
TIMER/SLEEP	Sleep Timer
SUBT.	Text Mode
EXPAND/PIP	PIP
TEXT/TTX	Text
EPG	Time, Subpage
REVEAL/PLAY	Still
TEXT STOP	ARC, Format
INFO/PAUSE	Index
RED	Red, PIP Progr. +
GREEN/REW	Green, PIP Progr. -
YELLOW	Yellow, PIP Swap
BLUE/FWD	Blue, PIP Input
MENU	MENU
UP	UP
EXIT/CANCEL	EXIT
LEFT	LEFT
OK	OK
RIGHT	RIGHT
SOUND/AUDIO	SSM
DOWN	DOWN
PICTURE	PSM
VOL+	VOL+
BACK	Quick View
CH+	CH+
VOL-	VOL-
TV/3D/DTV	PIP Position
CH-	CH-
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9
GUIDE/1./I/--	Scan
0	0
FAV/2./P/C	A.Swap